

**ATS Product SERIES**



Comparison Features	185	300 Group G	4000	7000
Intended Application	Residential Light Commercial	Commercial Light Industrial	Industrial	Mission Critical Critical Power
Ampere sizes available	100 - 400	30 - 3,000	30 - 4,000	30 - 4,000
Phases Available	Single	Single or Three	Single or Three	Single or Three
Pole Counts Available	2	2, 3 or 4	2, 3 or 4	2, 3 or 4
Low Voltage	220 - 240V	115 - 600V	115 - 600V	115 - 600V
Medium Voltage	N/A	N/A	N/A	5kV, 15kV
<b>Product Type</b>				
Open Transition Transfer Switch	Yes	Yes	Yes	Yes
Service Entrance Rated Transfer Switch	Yes	N/A	Yes	Yes
Power Transfer Load Center	Yes	N/A	N/A	Yes
Closed-Transition Transfer Switch	N/A	N/A	Yes	Yes
Delayed-Transition Transfer Switch	N/A	Yes	Yes	Yes
Bypass-Isolation Transfer Switch	N/A	N/A	N/A	Yes
Closed-Transition Bypass-Isolation TS	N/A	N/A	N/A	Yes
Delayed-Transition Bypass-Isolation TS	N/A	N/A	N/A	Yes
<b>Withstand and Close-On Ratings</b>				
WCR When Used With Any Circuit Breakers	N/A	N/A	10-100 kA	10-100 kA
WCR When Used With Specific Circuit Breakers	10kA -35kA	22-100kA	22-100kA	22-100kA
WCR when used with current limiting fuses	100-200kA	100-200kA	100-200kA	100-200kA
Short Time Withstand Rating	N/A	N/A	36-65kA	36-65kA
<b>Neutral Configuration</b>				
Solid	STD	STD	Yes	Yes
Switched	N/A	Yes	Yes	Yes
Overlapping	N/A	N/A	N/A	Yes
Ground Termination	Yes	Yes	Yes	Yes

Comparison Features	ATS Product SERIES			
	185	300 Group G	4000	7000
<b>Voltage and Frequency Settings</b>				
Phase Selection	Single Phase	Single or Three Phase	Single or Three Phase	Single or Three Phase
Pick up Normal Source Voltage	198 Volts	85 to 100%	85 to 100%	85 to 100%
Drop out Normal Source Voltage	154-187 Volts	70% to 98%	70% to 98%	70% to 98%
Pick up Emergency Source Voltage	198 Volts	85 to 100%	85 to 100%	85 to 100%
Drop out Emergency Source Voltage	165 Volts	70% to 98%	70% to 98%	70% to 98%
Frequency	50 or 60Hz	50 or 60 Hz	50 or 60 Hz	50 or 60 Hz
Pick Up Emergency Source Frequency	48 or 57Hz	95% Fixed	90 to 100%	90 to 100%
Drop out Emergency Source Frequency	43 or 51Hz	85% Fixed	85 to 98%	85 to 98%
Normal Overvoltage Trip	N/A	102 to 115%	102 to 115%	102 to 115%
Emergency Overvoltage Trip	N/A	102 to 115%	102 to 115%	102 to 115%
Normal Overfrequency Trip	N/A	101 to 110%	101 to 110%	101 to 110%
Emergency Overfrequency Trip	N/A	101 to 110%	101 to 110%	101 to 110%
Pick up Normal Source Frequency	N/A	86 to 100%	90 to 100%	90 to 100%
Drop out Normal Source Frequency	N/A	85 to 98%	85 to 98%	85 to 98%
Normal & Emergency Voltage Unbalance	N/A	N/A	Yes	Yes
<b>Time Delay Settings</b>				
Override Normal Source Momentary Outage	1 or 3 Seconds	0 to 6 Seconds	0 to 6 Seconds	0 to 6 Seconds
Transfer to Emergency	10 Seconds	0 to 60 Min 59 Sec	0 to 60 Minutes	0 to 60 Minutes
Re-transfer to Normal Utility Power Loss Mode	5 Minutes	0 to 60 Min 59 Sec	0 to 60 Minutes	0 to 60 Minutes
Engine Cool Down	2 or 5 Minutes	0 to 60 Min 59 Sec	0 to 60 Minutes	0 to 60 Minutes
Override Emergency Source Momentary Outage	4 Seconds	0 to 6 Seconds	0 to 60 Minutes	0 to 60 Minutes
Generator Exerciser	7 Day	7 Day	Programmable	Programmable
<b>Indication and Controls</b>				
Load Connected to Normal	Yes	Yes	Yes	Yes
Load Connected to Emergency	Yes	Yes	Yes	Yes
Normal Source Available	Yes	Yes	Yes	Yes
Emergency Source Available	Yes	Yes	Yes	Yes
Transfer Test Switch	Yes	Yes	Yes	Yes
Terminals For Remote Transfer Control	STD	STD	STD	STD
Bypass Time Delay Switch	Yes	Yes	Yes	Yes
Transfer Inhibit	N/A	Yes	Yes	Yes
In-Phase Monitor	N/A	Yes	Yes	Yes
Load Disconnect Contacts with Time Delay	N/A	STD	Optional	Optional
Event Log	N/A	Optional	Yes	Yes
Power Manager	N/A	Optional	Optional	Optional
Transfer Controls Lock Out	N/A	N/A	Yes	Optional
<b>Enclosures</b>				
Type 1	Yes	Yes	Yes	Yes
Type 3R	Yes	Yes	Yes	Yes
Type 4	N/A	Yes	Yes	Yes
Type 4X	N/A	Yes	Yes	Yes
Type 12	N/A	Yes	Yes	Yes
<b>Connectivity</b>				
RS-485 Serial	N/A	Yes	Yes	Yes
Ethernet	Yes	Yes	Yes	Yes
Modbus	N/A	Yes	Yes	Yes
Monitoring and Control via ASCO Products	Yes	Yes	Yes	Yes
<b>Optional Accessories</b>				
Optional	Field Kits Only	Expanded	Limited	Extensive