

	DP5000	DP7500	DP14000	W10000VE	WL12000HE	WL12000HE	WL12000HE 3PH	WL14000VE	WL16000VE	WL18000VE	WL22000VE	WL22000VE	W6010KE
ELECTRICAL DATA													
Running Watts	4,560	6,720	11,760	9,600	10,800	10,800	10,800	11,760	14,000	16,500	19,000	19,000	5,000
Running Amps	38/19	56/28	98/49	80/40	90/45	90/45	37.5/34/16	98/49	116/58	137.5/68.75	158/79	158/79	40/20
Motor Starting ⁽¹⁾	1.5 hp	2 hp	4 hp	3 hp	3.5 hp	3.5 hp	3.5	4 hp	4 hp	5 hp	6 hp	6 hp	1.5 hp
ENGINE DATA													
Make	Honda	Honda	B&S	B&S	Honda	Honda	Honda	B&S	Honda	B&S	B&S	B&S	Kohler
Model	GX270	GX390	Vanguard	Vanguard	GX630	GX630	GX630	Vanguard	iGX800	Vanguard	Vanguard	Vanguard	KD440
CARB	No	No	No	No	No	No	No	No	No	No	No	No	No
DBA @ 7 Meters	80.6	83.7	80	82.8	77	77	77	80	82	78	79	79	87.6
FUEL													
Fuel Tank	8 gal	8 gal	15 gal	7 gal	15 gal	15 gal	15 gal	15 gal	15 gal	15 gal	15 gal	15 gal	7 gal
Fuel Consumption (full load)	0.75 gal/hr	1.0 gal/hr	1.7 gal/hr	1.6 gal/hr	1.6 gal/hr	1.6 gal/hr	1.6 gal/hr	1.8 gal/hr	2.1 gal/hr	2.5 gal/hr	3.28 gal/hr	3.28 gal/hr	0.50 gal/hr
RECEPTACLES													
120 Volt Receptacles	(2) 5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI	(3) 5-20 GFCI	(3) 5-20 GFCI	(3) 5-20 GFCI (208-240V only)	(3) 5-20 GFCI	(3) 5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI	(2) 5-20 GFCI	(1) 5-20 GFCI L5-30 GFCI
120/240 Volt Receptacles	L14-30 GFCI	L14-30 GFCI	C6369 50A	14-50 GFCI	CS6369 50A	14-60	(Full Power) 208-240V - L21-30	CS6369 50A	CS6369 50A	14-60 L14-30 GFCI	(2) 14-50 GFCI	CS6369 50A L14-30 GFCI	L14-30 GFCI
240 Volt Receptacles	N/A	N/A	(2)L6-30 GFCI	L6-30 GFCI	L6-30 GFCI	L6-30 GFCI	480V - L19-30	(2)L6-30 GFCI	(2)L6-30 GFCI	L6-30 GFCI	L6-30 GFCI	ANDERSON	N/A

Notes: (1) Code G capacitor start motor. (2) Electric start models include battery rack and cables. Battery not included

Commercial Engines

Honda GX and Briggs & Stratton Vanguard engines are known for their dependability and performance.

Rugged Design

Engineered and built tough with steel and powder coat paint.



OPTIONAL ACCESSORIES

DOLLY KITS

- Two-Wheel - 5-10kW
- Four-Wheel - 12-22kW



MAINTENANCE KIT

- Premium synthetic 5W-30 oil
- Sta-bil fuel stabilizer
- Spark plug
- Air filter



GENERATOR COVER

- Made of heavy canvas
- Weather resistant



BATTERY

- Interstate, fully sealed batteries



BATTERY CHARGER

- Smart 3 stage 1.5 Amps trickle charger



PLUGS

- L14-30 30 A
- 14-60 60A
- CS6365 50A
- 14-50 50A
- Anderson Plug
- 30A 20ft cord set



GENERATOR EXPERTS

 An American Company.

We produce our products in our 200,000ft² facility located in Le Center, Minnesota, equipped with modern engineering, fabrication and assembly capabilities.



Why WINCO

WINCO is known for portable generators, especially the “Big Dog” industrial generators that have been the gold standard for large air-cooled power for almost two decades! Commercial engines and a rugged design make our generators dependable, durable, and just plain awesome.

Distributed By:

WINCO
GENERATORS
AN AMERICAN COMPANY
www.wincogen.com

225 S. Cordova Ave • Le Center, MN 56057

L-1001/F



INDUSTRIAL PORTABLE
& VEHICLE MOUNTED
GENERATORS

EMERGEN-C

EC6010KE EC18000VE EC22000VE

ELECTRICAL DATA			
Running Watts	5,000	15,000	19,000
Running Amps	40/20	125/62.5	158/79 1-PH
Motor Starting ⁽¹⁾	2 HP	5 hp	6 hp
ENGINE DATA			
Make	Kohler	B&S	B&S
Model	KD440	Vanguard	Vanguard
Fuel Type	Diesel	Gasoline	Gasoline
CARB	No	No	No
DBA @ 7 Meters	87.6	79	79
FUEL			
Fuel Tank	N/A	Optional	Optional
Fuel Consumption ⁽²⁾	0.50 gal/hr	2.69 gal/hr	3.28 gal/hr

RECEPTACLES			
120/240V Receptacles	L14-30 30A	14-60 60A	Hard Wired
Notes: (1) Code G capacitor start motor. (2) Fuel consumption is estimated at full load.			

Open Skid

The open skid design creates easy installation in a rig or trailer.

