



XP13000E

PORTABLE GAS GENERATOR

13,000 STARTING WATTS • 10,500 RUNNING WATTS






XP13000E

PORTABLE GAS GENERATOR

FEATURES



OUTLETS



X2
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock



X1
120/240V
30A Twist
Lock



X1
120/240V
50A Heavy
Duty Outlet

SPECS

Watts	13,000 (peak) • 10,500 (running)
Engine	OHV 500cc
Amperage	87.50A / 43.758A
Voltage	120V / 240VAC & 12VDC
Frequency	60 Hz
Fuel Type	Gasoline
Runtime at 50% Load	8.5 hrs
Start Type	Electric / Recoil