



# XP13000EH

**DUAL FUEL PORTABLE GENERATOR**  
 13,000 STARTING WATTS • 10,500 RUNNING WATTS






# XP13000EH

DUAL FUEL PORTABLE GENERATOR

## FEATURES



## OUTLETS



**X2**  
120V 20A  
GFCI Outlet



**X1**  
120V 30A  
Twist Lock



**X1**  
120/240V  
30A Twist  
Lock



**X1**  
120/240V  
50A Heavy  
Duty Outlet

## SPECS

<b>Watts (Gasoline)</b>	13,000 (peak) • 10,500 (running)
<b>Watts (Propane)</b>	12,350 (peak) • 9,975 (running)
<b>Engine</b>	OHV 500cc
<b>Amperage</b>	87.50A / 43.75A
<b>Voltage</b>	120V / 240VAC & 12VDC
<b>Fuel Type</b>	Gasoline / Propane
<b>Runtime (Gasoline) at 50% Load</b>	8.5 hrs
<b>Runtime (Propane) at 50% Load</b>	6.5 hrs