



XP15000E

PORTABLE GAS GENERATOR

15,000 STARTING WATTS • 12,500 RUNNING WATTS






XP15000E

PORTABLE GAS GENERATOR

FEATURES



OUTLETS



X4
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock



X1
120/240V
30A Twist
Lock



X1
120/240V
50A Heavy
Duty Outlet

SPECS

Watts	15,000 (peak) • 12,500 (running)
Engine	V-Twin 713cc
Amperage	104.00A / 52.00A
Voltage	120V / 240VAC
Frequency	60 Hz
Fuel Type	Gasoline
Runtime at 50% Load	8.83 hrs
Start Type	Electric