



# XP15000EH

DUAL FUEL PORTABLE GENERATOR

15,000 STARTING WATTS • 12,500 RUNNING WATTS






# XP15000EH

DUAL FUEL PORTABLE GENERATOR

## FEATURES



## OUTLETS



**X4**  
120V 20A  
GFCI Outlet



**X1**  
120V 30A  
Twist Lock



**X1**  
120/240V  
30A Twist  
Lock



**X1**  
120/240V  
50A Heavy  
Duty Outlet

## SPECS

<b>Watts (Gasoline)</b>	15,000 (peak) • 12,500 (running)
<b>Watts (Propane)</b>	14,250 (peak) • 11,400 (running)
<b>Engine</b>	713cc V-Twin
<b>Amperage</b>	104.00A / 52.00A
<b>Voltage</b>	120V / 240VAC
<b>Fuel Type</b>	Gasoline / Propane
<b>Runtime (Gasoline) at 50% Load</b>	9.03 hrs
<b>Runtime (Propane) at 50% Load</b>	8.58 hrs