



XP5500EH

DUAL FUEL PORTABLE GENERATOR
5,500 STARTING WATTS • 4,500 RUNNING WATTS






XP5500EH

DUAL FUEL PORTABLE GENERATOR

FEATURES



OUTLETS



X2
120V 20A
GFCI Outlet



X1
120/240V
30A Twist
Lock



DOUBLE THE
120V AMPERAGE

SPECS

Watts (Gasoline)	5,500 (peak) • 4,500 (running)
Watts (Propane)	5,225 (peak) • 4,275 (running)
Engine	OHV 424cc
Amperage	37.50A / 18.75A
Voltage	120V / 240VAC & 12VDC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	9 hrs
Runtime (Propane) at 50% Load	8 hrs