



XP5500HX

DUAL FUEL PORTABLE GENERATOR

5,500 STARTING WATTS • 4,500 RUNNING WATTS



FEATURING CO ALERT TECHNOLOGY





XP5500HX

DUAL FUEL PORTABLE GENERATOR


FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- All-Copper Windings
- Digital Command Center
- Fully-Loaded Power Panel
- Exclusive MX2 Switch
- Low Oil Sensor



CO ALERT TECHNOLOGY

OUTLETS



X2
120V 20A
GFCI Outlet



X1
120/240V 30A
Twist Lock



X1
2.1A 1.0A
USB Outlet



DOUBLE THE
120V AMPERAGE

SPECS

Watts (Gasoline)	5,500 (peak) • 4,500 (running)
Watts (Propane)	5,225 (peak) • 4,275 (running)
Engine	OHV 210cc
Amperage	37.50A / 18.75A
Voltage	120V / 240VAC & 5VDC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	8.82 hrs
Runtime (Propane) at 50% Load	7.63 hrs