

Upgradeable Manual Transfer Switch

30 AMP AMP KITS For Portable Generators

HOMELINK™ 



30 AMP Pre-wired Switch Kit
Model 6853



30 AMP Pre-wired Switch
Model 6852



30 AMP Pre-wired Switch Kit
Model 6854



features

Versatile: Can be upgraded later for use with a Generac Home Standby Generator (max 11 kW).

Power indicator lights: Displays when you have utility power or generator power.

Safe: Prevents dangerous back-feeding to avoid injuring utility line workers.

Powers hard-wired circuits: Directly powers hard-wired appliances such as your furnace, well pump, and lights.

Easy to maintain and expand: Interchangeable type circuit breakers make it easy to reconfigure, replace, or expand the circuits in your switch.

30 AMP KITS

Model	6852	6853	6854
Max Amps @ 240V	30 Amp	30 Amp	30 Amp
Upgradeable for use with a Generac Home Standby Generator (up to 11 kW)	Yes	Yes	Yes
Enclosure	Indoor (NEMA 1)	Indoor (NEMA 1)	Indoor (NEMA 1)
Circuits Provided	8	8	8
Max # Circuits	10	10	10
Included Breakers	1- 30 Amp 2- pole 1- 20 Amp 1- pole 5- 15 Amp 1- pole	1- 30 Amp 2- pole 1- 20 Amp 1- pole 5- 15 Amp 1- pole	1- 30 Amp 2- pole 1- 20 Amp 1- pole 5- 15 Amp 1- pole
Accepts Arc-Fault and GFCI Breakers	Yes	Yes	Yes
Prewired	Yes	Yes	Yes
Required Main Breaker in Load Center (provided by installer)	50 Amp 2 pole	50 Amp 2 pole	50 Amp 2 pole
Male Inlet Configuration Outdoor Power Inlet Box	L14-30 NEMA 3R	L14-30 NEMA 3R	L14-30 NEMA 3R
Kit Contents	<ul style="list-style-type: none"> • Transfer Switch • Install manual, wiring harness, conduit and fittings 	<ul style="list-style-type: none"> • Transfer Switch • Cord: 10 ft. 10/4 with L14-30 male and female ends • Power Inlet Box: 30 Amp resin (must be hardwired) • Install manual, wiring harness, conduit and fittings 	<ul style="list-style-type: none"> • Transfer Switch • Cord: 10 ft. 10/4 with L14-30 male and female ends • Power Inlet Box: 30 Amp aluminum (must be hardwired) • Install manual, wiring harness, conduit and fittings
Switch Dimensions	15.4" L x 15.8" H x 4"D	15.4" L x 15.8" H x 4"D	15.4" L x 15.8" H x 4"D
Shipping Dimensions	25.8" L x 18.7" W x 7.8" H	25.8" L x 18.7" W x 7.8" H	25.8" L x 18.7" W x 7.8" H
Shipping Weight (lbs).	26	27.5	27.2
UPC codes	696471068528	696471068535	696471068542
Compatible With	GP5500, GP6500E, XG6500, XG7000E, XP6500E, XP8000E, XT8000E, RS5000, RS7000E	GP5500, GP6500E, XG6500, XG7000E, XP6500E, XP8000E, XT8000E, RS5000, RS7000E	GP5500, GP6500E, XG6500, XG7000E, XP6500E, XP8000E, XT8000E, RS5000, RS7000E
Warranty	5 Year Limited	5 Year Limited	5 Year Limited